


TA790GX A2+ Motherboard



• AMD AM2+/AM2 Platform

• Support latest AMD Phenom X4 , X3 / Athlon /Sempron processors

- AMD 140W processor support
- AMD 790GX Chipset with ATI Radeon HD 3300 Graphics
- On Board 64MB DDR2 Side-Port memory
- Dual-Channel DDR2 -1066/800/667/533
- ATI Hybrid Graphics Support
- Superior scaling with ATI CrossFireX technology
- Integrated HDMI/DVI interface with HDCP Support 1080P HD Video Experience
- AMD OverDrive Utility Support
- AMD OverDrive[™] with ACC feature (Advanced Clock Calibration) supported

TA790GX A2+ Specifcation

CPU SUPPORT	AMD Phenom [™] X4 Processor AMD Phenom [™] X3 Processor AMD Athlon [™] X2 Dual-Core Processor AMD Athlon [™] 64 X2 Dual-Core Processor AMD Athlon [™] 64 FX Processor AMD Athlon [™] 64 Processor AMD Sempron [™] Processor
НТ	Support HT 5.2G
MEMORY	Support Dual Channel DDR2 533/667/800/1066(1066 by AM2+ CPU) MHz 4 x DDR2 DIMM Memory Slot Max. Supports up to 16GB Memory
INTEGRATED VIDEO	ATI Radeon [™] HD3300 Graphics with 64MB Sideport memory, Max. Memory Share Up to 512 MB Support ATI Hybrid Crossfire

STORAGE	6 x SATA II Connector 1 x IDE Connector Support SATA RAID: 0,1,5,10
LAN	Realtek RTL8111C - 10/100/1000 Controller
AUDIO CODEC	Realtek ALC888 8+2 Channel HD Audio
USB	4 x USB 2.0 Port 3 x USB 2.0 Header
EXPANSION SLOT	2 x PCI-E 2.0 x16 Slot(CFX x8) 2 x PCI-E 2.0 x1 Slot 2 x PCI Slot
REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 4 x USB 2.0 Port 1 x HDMI Connector 1 x DVI Connector 1 x VGA Port 1 x LAN Port 6 x Audio Jacks
INTERNAL I/O	3 x USB 2.0 Header 6 x SATA II Connector (3Gb/s) 1 x IDE Connector 1 x Floppy Connector 1 x Front Audio Header 1 x Front Panel Header 1 x CD-IN Header 1 x CD-IN Header 1 x S/PDIF-Out Header 1 x CPU Fan Connector 1 x North Bridge FAN Header 1 x System Fan Connector 1 x COM Port Header 1 x Printer Port Header
DIMENSION	ATX Form Factor Dimension: 30.5cm X 22.5cm (W x L)
OS SUPPORT	Supports Windows XP / Vista
ACCESSORIES	1 x IDE Cable 2 x SATA Cable 1 x SATA Power Cable 1 x I/O Shield 1 x Shadow Card 1 x Fully Setup Driver CD 1 x User Manual

Supports AOD ACC Supports AM3/AM2+ Supports Solid capacitor Supports Fanless Supports Clean-Tone Supports Rapid Switch Supports Rapid Debug BIO-FLASHER

TA790GX A2+ OVERVIEW

CPU-Chipset







AM2¹

AM3/AM2+ Support

Supporting upcoming AMD Socket AM3/AM2+ 45nm processors, it delivers better overclocking capabilities and reduces power consumption. Moreover, AM3 CPU supports both DDR2 /DDR3 memory module and accelerates data transfer rate by up to 5200MT/s via HyperTransport 3.0 technology.

AMD HD ! Experience

AMD's HD video solution presents a new era of HD content and HD-related products that will revolutionize your viewing experience. AMD desktop solution can provide a full HD experience with support of the latest and most demanding formats, including VC-1, MPEG-2 and H.264 on a mainstream PC. It lets consumers enjoy a smooth HD viewing experience with less lag, stalling and dropped scenes in the latest Blu-ray titles. AMD HD! Experience realizes a convergence of digital consumer electronics and PCs with HD peripherals.

* AMD HD! Experience is highly popular in the Japanese market.

Socket AM2+ Phenom processors Support

Supporting AMD® Socket AM2+ Quad /Triple Core processors, it delivers better overclocking capabilities with low power consumption. Phenom processor features dual-channel DDR2 1066 memory support and accelerates data transfer rate by up to 5200MT/s via HyperTransport[™] 3.0 system bus.



Video+







HyperTransport 3.0 Support

It provides a maximum 5200MT/s via HyperTransport[™] 3.0 system bus and significantly improves system efficiency for a high performance and faster desktop.

ATI CrossFire X[™] Technology

ATI CrossFireX[™] is the ultimate multi-GPU performance gaming platform. With gamedominating power, ATI CrossFireX technology enables two or more discrete graphics processors to work together to improve system performance. It supports up to four ATI Radeon[™] HD graphics cards, making it the most scalable gaming platform ever!

64MB SidePort

The 64MB side-port memory onboard can accelerate 3D gaming performance easily. Sideport memory is similar to onboard graphics memory buffer. When enabled, it could increase the 3D performance by another 10% or more.

Integrated HDMI with HDCP

Onboard HDMI connector allows full video & audio support. It has industry-leading high definition video quality.

Speed+



PCI Express 2.0 Support

PCI Express 2.0 bus architecture offers a futureproofing bridge to tomorrow's most bandwidthdriven games and 3D applications by maximizing 5 GT/s of bandwidth. PCI Express 2.0 motherboards are fully backwards compatible with existing PCI Express products for broad support of PC peripherals.



MX SUITE

MEDIA SOLUTION











MX SUITE

As an Biostar customer you can download MAGIX multimedia tools designed to enhance your music, videos and photos for free. From music and website creation to video editing and photo management. Four products that cover all of your multimedia needs. Simply do more with your media than you ever thought possible.

Simplitec

"Simplitec" offers premium solutions to ensure your PC is faster, more reliable and free of security gaps - automatically or with customized setups. "Simplitec" is a free bundle software to scan your computer for problems and offers a professional solution for each problem to put your PC back in top form.

BIO-Flasher

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.

BIO-ReLife

BIO-ReLife Technology lets you recover crashed BIOS data from a USB flash pen driver that stores new BIOS file. This practical BIOS utility can restore your system and recover from a BIOS crash situation.

eHot-Line Utiltiy

Integrated e-service automatically sends your technical support request to Biostar Globe tech support without any delay.

Rapid Switch

No more meddling with the power and reset jumpers onboard. The power and reset buttons are already built onboard. It is convenient for DIY users to test the board without short-circuiting the wrong pins.



Rapid Debug

There is no need to check any H/W installation error. Onboard LED indicator answers the question for the user.

*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!