

Hi-Fi A85W 3D Motherboard



- Supported Socket FM2 processors AMD A-series/ E2-series processor
- Supported AMD Mutil Core(x4,x2)
- AMD 100W processor support
- AMD A85X Chipset
- 4 DIMM supported DDR3-2400(OC)/ 2133/ 1866/ 1600/ 1333/ 1066/ 800
- \bullet Supported SATA 6Gb/s 2X speed than current SATA 3G
- Supported USB 3.0
- AMD Dual Graphics Technology
- 100% X.D.C solid capacitor
- BIOSTAR Puro Hi-Fi 3D

Hi-Fi A85W 3D Specifcation

CPU SUPPORT	AMD A10 Processor AMD A8 Processor AMD A6 Processor AMD A4 Processor AMD E2 Processor AMD Athlon [™] II X4 Processor Maximum CPU TDP (Thermal Design Power) : 100Watt
MEMORY	Support Dual Channel DDR3 2400(OC)/2133/1866/1600/1333/1066/800 MHz 4 x DDR3 DIMM Memory Slot Max. Supports up to 64GB Memory
INTEGRATED VIDEO	By CPU model AMD Dual Graphics Technology Supports DX11 Supports HDCP
STORAGE	8 x SATA III Connector Support SATA RAID: 0,1,5,10

LAN	Realtek RTL8111G - 10/100/1000 Controller
AUDIO CODEC	Realtek ALC892 8-Channel Blu-ray Audio
USB	2 x USB 3.0 Port 1 x USB 3.0 Header 4 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	2 x PCI-E 2.0 x16 Slot(x16 + x4) 2 x PCI-E 2.0 x1 Slot 2 x PCI Slot
REAR I/O	1 x PS/2 Keyboard 2 x USB 3.0 Port 4 x USB 2.0 Port 1 x HDMI Connector 1 x DVI Connector 1 x VGA Port 1 x LAN Port 6 x Audio Jacks
INTERNAL I/O	1 x USB 3.0 Header 2 x USB 2.0 Header 8 x SATA III Connector (6Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x S/PDIF-Out Header 1 x CPU Fan Connector 2 x System Fan Connector 1 x CIR Header 1 x COM Port Header
H/W MONITORING	CPU / System Temperature Monitoring CPU / System Fan Monitoring Smart / Manual CPU Fan Control System Voltage Monitoring
DIMENSION	ATX Form Factor Dimension: 30.5cm x 23.5cm (W x L)
OS SUPPORT	Supports Windows XP / Vista / 7 / 8 / 10
BUNDLE SOFTWARE	BIO-Remote2 BIO-Remote Smart Speed LAN
ACCESSORIES	4 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x User Manual

Windows 8 Compatible Supports PURO Hi-Fi 3D Supports 100% Solid capacitor Supports Rapid Switch Rapid Debug3 BIO-FLASHER Supports Charger Booster Supports BIOS Online Update

Hi-Fi A85W 3D OVERVIEW

Audio+







Blu-ray Audio

Upgrading your Audio performance in the easiest way is choosing BIOSTAR ultimate Motherboard. It does support Blu-ray audio DRM (compatible driver/software) and provide the higher audio output of 24 bit/ 192KHz than the 16 bit/ 48KHz from the normal MB. You will experience the high quality sound effect with pure Blu-Ray Audio.

Hi-Fi AMP 3D

With the built-in new generation 3D amplifier, Biostar Hi-Fi 3D motherboard can drive major highend headphones with over 100dB loads and up to 600ohm impedance. It allows you enjoy a fuller range of dynamic sound with crisper details and less distortion when you are using any headphones.

Smart Ear 3D

Smart Ear 3D provides true reproduction of virtual 3D space using any headphones! It delivers the true 3D sounds for music, movies and also games. It's fantastically, especially if you've never experienced this kind of acoustic phenomenon before.











Hi-Fi Pre AMP

Hi-Fi 3D Technology is built-in power amplifier to boost the speaker volume. It will increase double volume level with high-quality HD audio output. Hi-Fi 3D Technology not only improves on the headphone but also enhances your speakers' sound volume.

Hi-Fi preamp can boost the line level audio signals from analog and digital sources to levels that a power amplifier can detect and boost again to successfully power up the loadspeaker.

3D Sound Fields

The six types of 3D Sound Fields are including Hi-Fi Theater, Hi-Fi Hall, Hi-Fi Game spots, Hi-Fi Studio, Hi-Fi Conference and Hi-Fi Bistro for your different applications. Biostar Hi-Fi 3D technology involves the virtaul placement of sound sources anywhere in 3 dimensional spaces, including behind, above or below.

Hi-V Caps

Hi-V Caps is "Metalized Polypropylene Film Capacitor" for each audio channel circuit. The customized audio capacitors deliver low noise, low distortion and wide bandwidth to achieve the highest sound resolution and sound expansion.

Hi-Fi Power

Audio power is an important factor in audio quality. Most AV equipment isolates the power supply for each analog and digital signal to gather highquality sound reproduction. Equipped with BIOSTAR Hi-Fi Power technology, it will utilize audio components with independent power design for a significant reduction in electronic noise and superb sound quality.

Hi-Fi Ground

BIOSTAR Hi-Fi Ground (Golden Line) is noiseblocking multi-layer PCB design to isolates analog audio signals from digital sources. Unique PCB layout is ideal for exceptional clarity and high fidelity sound.



Hi-Fi 110dB+

Embrace exceptional sound quality for the win with 110dB SNR and stylish and efficient EMI shield blocks electromagnetic interference to help provide cleaner audio. It has achieved a signal-t--noise ratio (SNR) of 110dB, yielding almost lossless audio form rear audio connectors.

Video+







ATI CrossFire X[™] Technology

ATI CrossFireX[™] is the ultimate multi-GPU performance gaming platform. With gamedominating power, ATI CrossFireX technology enables two or more discrete graphics processors to work together to improve system performance. It supports up to four ATI Radeon[™] HD graphics cards, making it the most scalable gaming platform ever!

HDMI with HDCP {INS_STR}

HDMI allows full video & audio support via standard DVI output. It has industry-leading high definition video quality.

SmartSpeedLAN

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing.You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.









USB 3.0

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.

Charger Booster

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.

SATAIII 6Gbps

SATAIII 6Gbps provides a higher bandwidth to retrieve and transfer HD media. With this super speed data transfer, SATAIII allows an incredible data boost which is 2x faster than the SATA II.

T-Overclocker

T-overclocker presents a simple Windows-based system performance enhancement and utility management. It features several powerful yet easy to use tools such as overclocking for system performance enhancement, CPU and memory special enhancement, a smart-fan control for managing fan speed control of both CPU cooling fan, north-bridge chipset cooling fan, PC health for monitoring system status, and pre-set OC modes for easy OC.

Durable+



100% Solid Caps

With armor-plated Biostar Technology, all capacitors are placed with 100% solid capacitors that have a lasting life cycle, durability and stability for crucial components.

Protection+



High Quality ESD

BIOSTAR Hi-Fi series motherboards provide high quality ESD (Electro-Static Discharge) solution for its front I/O panel. This function prevents static electricity and reduces the damage to the motherboards when you are plugging or unplugging your headphone.

DIY+









UEFI BIOS

Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.

BIO-Remote 2

BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.

BIO-Flasher

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.

Rapid Debug 2

There is no need to check any H/W installation error. Onboard LED indicator shows 6 kinds of messages: CPU power, MB power, CPU, memory and PCI-E, SATA. *The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!