

TZ68K+ Motherboard



- Supports the Intel 2nd generation Core i7 and Core i5 processors in the 1155 package
- Intel Z68 single chip architecture
- Support 4-DIMM DDR3-2200(OC)/2133(OC)/1866(OC)/1600(OC)/1333 up to 32G maximum capacity
- Support SATA 6Gb/s 2X speed than current SATA 3G
- Support Intel Smart Response Technology (It is required to update both "BIOS" and "Intel® RST Driver" to the latest version)
- Support USB 3.0
- 100% X.D.C solid capacitor
- BIOSSTAR G.P.U (Green Power Utility) Technology for Energy Saving
- BIOSSTAR Toverclocker utility

TZ68K+ Specification

CPU SUPPORT	Intel® Core™ i7 LGA 1155 Processor Intel® Core™ i5 LGA 1155 Processor Intel® Core™ i3 LGA 1155 Processor Maximum CPU TDP (Thermal Design Power) : 95Watt
MEMORY	Support Dual Channel DDR3 2200(OC)/2133(OC)/1866(OC)/1600(OC)/1333/1066 MHz 4 x DDR3 DIMM Memory Slot Max. Supports up to 32GB Memory It is recommended to install memory module on the red DDR3 DIMM slot (DDR3_A2 or DDR3_B2) to boot the system.
INTEGRATED VIDEO	By CPU model
STORAGE	2 x SATA III Connector 4 x SATA II Connector Support SATA RAID: 0,1,5,10 Support Intel Smart Response Technology

LAN	Realtek RTL8111E - 10/100/1000 Controller
AUDIO CODEC	Realtek ALC892 6-Channel Blu-ray Audio
USB	ASMedia ASM1042 USB 3.0 controller 2 x USB 3.0 Port 2 x USB 2.0 Port 3 x USB 2.0 Header
EXPANSION SLOT	2 x PCI-E 2.0 x16 Slot(x16 + x4) 1 x PCI-E 2.0 x1 Slot 2 x PCI Slot
REAR I/O	1 x PS/2 Keyboard 2 x USB 3.0 Port 2 x USB 2.0 Port 1 x HDMI Connector 1 x DVI Connector 1 x VGA Port 1 x LAN Port 3 x Audio Jacks
INTERNAL I/O	3 x USB 2.0 Header 2 x SATA III Connector (6Gb/s) 4 x SATA II Connector (3Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x S/PDIF-Out Header 1 x CPU Fan Connector 2 x System Fan Connector 1 x CIR Header 1 x COM Port Header 1 x Printer Port Header
DIMENSION	ATX Form Factor Dimension: 30.5 cm x 23 cm (W x L)
OS SUPPORT	Supports Windows XP / Vista / 7
BUNDLE SOFTWARE	BIO-Remote2 BIO-Remote
ACCESSORIES	4 x SATA Cable 1 x I/O Shield 1 x Fully Setup Driver CD 1 x User Manual

FEATURES	Supports uEFI GUI Interface BIOS Windows 7 Compatible Supports 100% Solid capacitor Supports Rapid Switch Supports Rapid Debug Supports Toverclocker OC software Supports GPU Supports Charger Booster Supports BIOS Online Update
----------	--

TZ68K+ OVERVIEW

CPU-Chipset



Intel LGA 1155 2nd Generation Intel Core™ Processors support

2nd Generation Intel® Core™ Processors with New 32nm Intel® micro architecture / Impressive leap in energy-efficient performance / Optimized Intel Turbo Boost Technology and Intel Hyper-Threading Technology / Significant advances in visual and 3D graphics capabilities / New Intel RAVX instructions for enhanced floating point intensive application performance.

Audio+



Blu-ray Audio

Upgrading your Audio performance in the easiest way is choosing BIOSTAR ultimate Motherboard. It does support Blu-ray audio DRM (compatible driver/software) and provide the higher audio output of 24 bit/ 192KHz than the 16 bit/ 48KHz from the normal MB. You will experience the high quality sound effect with pure Blu-Ray Audio.

Video+



ATI CrossFire X™ Technology

ATI CrossFireX™ is the ultimate multi-GPU performance gaming platform. With game-dominating power, ATI CrossFireX technology enables two or more discrete graphics processors to work together to improve system performance. It supports up to four ATI Radeon™ HD graphics cards, making it the most scalable gaming platform ever!



Virtu GPU Virtualization Software

Graphics technology found in an integrated GPU, an Intel Sandy Bridge CPU or on a discrete 3D graphics card have a variety of different, yet important, graphics, media, gaming and power saving benefits. In comes Virtu, the first GPU virtualization software that makes it all accessible and eliminates the need to choose.

Speed+



USB 3.0

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.



Charger Booster

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.



SATAIII 6Gbps

SATAIII 6Gbps provides a higher bandwidth to retrieve and transfer HD media. With this super speed data transfer, SATAIII allows an incredible data boost which is 2x faster than the SATA II.



T-Overclocker

T-overclocker presents a simple Windows-based system performance enhancement and utility management. It features several powerful yet easy to use tools such as overclocking for system performance enhancement, CPU and memory special enhancement, a smart-fan control for managing fan speed control of both CPU cooling fan, north-bridge chipset cooling fan, PC health for monitoring system status, and pre-set OC modes for easy OC.



Dual Channel DDR3

It supports 2 or 4 DIMM Slots DDR3 memory that features data transfer rates of DDR3 2000(O.C.)/1800(O.C.)/1600/1333. The processor support 2 memory channels and setting the memory multiplier, allows selection of the channel speed. These clearly uplift the band width and boost the overall system performance.

Durable+



8 Phase Power Design

8-phase power design gives unparalleled overclocking ability and the lowest temperature to reach maximum performance level.



100% Solid Caps

With armor-plated Biostar Technology, all capacitors are placed with 100% solid capacitors that have a lasting life cycle, durability and stability for crucial components.



G.P.U (Green Power Utility)

BIOSTAR G.P.U (Green Power Utility) is a new function that enhances energy efficiency by disabling extra phases while CPU is under light loading. It integrates a friendly GUI to monitor the resourcing and response of your CPU thus optimizing the power saving function in your system. G.P.U. constantly sets up the best power efficiency in your system, be it for heavy 3D gaming, Internet or MSN chatting.

Protection+



BullGuard Internet Security (90 days FREE trial)

BullGuard Internet Security comes with the broadest line-up of internet security features on the market, including: a cutting-edge dual Antivirus engine, Online Backup for your precious files, PC Tune Up to speed up your system, a Game Mode for a seamless gaming experience, Parental Control, Firewall, Safe Browsing and many more. Make the most of your digital life with Bullguard!

DIY+



UEFI BIOS

Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.



BIO-Remote 2


BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.

MX SUITE
THE ALL-IN-ONE
MEDIA SOLUTION

**FREE
DOWNLOAD**

MX SUITE

As an Biostar customer you can download MAGIX multimedia tools designed to enhance your music, videos and photos for free. From music and website creation to video editing and photo management. Four products that cover all of your multimedia needs. Simply do more with your media than you ever thought possible.



Simplitec

"Simplitec" offers premium solutions to ensure your PC is faster, more reliable and free of security gaps - automatically or with customized setups. "Simplitec" is a free bundle software to scan your computer for problems and offers a professional solution for each problem to put your PC back in top form.



Rapid Switch

No more meddling with the power and reset jumpers onboard. The power and reset buttons are already built onboard. It is convenient for DIY users to test the board without short-circuiting the wrong pins.



Rapid Debug

There is no need to check any H/W installation error. Onboard LED indicator answers the question for the user.

***The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!**