

# J1900MH Motherboard



- On board Intel Quad-core Celeron J1900(2.0 GHz) processor
- Supports 2 DIMM of DDR3L 1333MHz up to 16G maximum capacity
- Intel HD Graphics
- Supports BIO-Remote 2 Technology
- Supports Charger Booster Technology

# J1900MH Specifcation

CPU	Intel® Celeron J1900(2.0 GHz) Quad-Core Processor
MEMORY	Support Dual Channel DDR3L 1333 MHz 2 x DDR3 DIMM Memory Slot Max. Supports up to 16GB Memory
INTEGRATED VIDEO	Intel HD Graphics Supports DX11 Supports HDCP
STORAGE	2 x SATA II Connector
LAN	Realtek RTL8111G - 10/100/1000Mb/s Controller
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio
USB	1 x USB 3.0 Port 2 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 2.0 x16 Slot 1 x PCI-E x1 Slot

REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 1 x USB 3.0 Port 2 x USB 2.0 Port 1 x HDMI Connector 1 x VGA Port 1 x LAN Port 3 x Audio Jacks
INTERNAL I/O	2 x USB 2.0 Header 2 x SATA II Connector (3Gb/s) 1 x Front Audio Header 1 x Front Panel Header 2 x System Fan Connector 1 x COM Port Header 1 x Printer Port Header
H/W MONITORING	CPU / System Temperature Monitoring System Fan Monitoring System Voltage Monitoring
DIMENSION	Micro ATX Form Factor Dimension: 19cm x 18.8cm ( W x L )
OS SUPPORT	Supports Windows 7 / 8 / 8.1 / 10(x64)
BUNDLE SOFTWARE	BIO-Remote2 Smart Speed LAN
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide
FEATURES	Supports Solid capacitor BIO-FLASHER Supports Charger Booster
J1900MH OVERVIEW	

# **CPU-Chipset**



# Intel Celeron J1900 Quad Core processor

The Intel® Celeron J1900(2M Cache, up to 2.42 GHz) is a quad-core processor. Although both parts are clocked the same, at 2 GHz, the J1900 also incorporates Burst Technology, that can boost operating frequency up to 2.41 GHz. The maximum GPU frequency was also increased on the J1900 to 854 MHz, while the base GPU speed stayed at 688 MHz. The rest of the specs have not changed.It supports DDR3L-1333 memory and fit into 10 Watt thermal envelope.

# Audio+



#### **HD** Audio

Provides high quality sound with minimal loss of audio fidelity.

#### Video+



#### **HDMI 3D Visual**

The HDMI 3D Visual provides a level of interoperability for devices designed to deliver 3D content over the HDMI connection. The latest HDMI Specification adds key enhancements to support the market requirements for bringing broadcast 3D content into the home featuring key enhancements for 3D applications including the addition of mandatory 3D formats for broadcast content.



#### **DX11**

Direct3D 11 enables Direct3D 10 APIs and Direct3D 11 APIs to use one underlying rendering device. And it allows developers to achieve a high speed, fully conformant software rasterizer.

# Speed+



## **SmartSpeedLAN**

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing. You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.



#### **USB 3.0**

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.



## **Charger Booster**

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.

## Durable+



### Moistureproof of PCB

The popularity of PC usage and working environment is getting deteriorating and moist (rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture proof.



#### Low RdsOn P-Pak MOS

Low resistance design can significantly reduce the current out of energy loss. Low temperature, small size, excellent thermal conductivity.

#### Protection+





#### **ESD Protection**

ESD (Electrostatic Discharge) is the major factor to destroy the PC by electrical overstress (EOS) condition. ESD occurred by PC users when touch any devices connect to a PC, which may result in damage to the motherboard or parts. ESD protection is designed to protect the motherboard and equipment from damage by EOS.

## **USB Polyswitch**

On board dedicated power fuse to help prevent USB port failure. It prevents USB Port overcurrent and safe guard your system and device lifespan.





#### **BIOS Virus Protection**

When enabled, the BIOS will protect the boot sector and partition table by halting the system and flashing a warning message whether there's an attempt to write to these areas.



#### OC / OV / OH Protection

OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.



# BullGuard Internet Security (90 days FREE trial)

BullGuard Internet Security comes with the broadest line-up of internet security features on the market, including: a cutting-edge dual Antivirus engine, Online Backup for your precious files, PC Tune Up to speed up your system, a Game Mode for a seamless gaming experience, Parental Control, Firewall, Safe Browsing and many more. Make the most of your digital life with Bullguard!

# DIY+



#### **UEFI BIOS**

Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.



#### Header Zone

Users can easily assemble their own computer, a simple-swap data discs and other accessories.



#### **BIO-Remote 2**

BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.



#### **BIO-Flasher**

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.

\*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!

